

APPARATUS FOR REDUCING POWER SUPPLY NOISE
IN AN INTEGRATED CIRCUIT

Cross-Reference To Related Applications

[0001] This application is a continuation-in-part of U.S. application serial no. 10/003,596, filed October 30, 2001, which is a divisional of U.S. application serial no. 09/484,600, filed January 18, 2000, now U.S. Patent No. 6,339,338 B1.

now US Patent No. 6456103

Background of the Invention

Field of the Invention

[0002] The present invention relates in general to systems for testing integrated circuits and in particular to an apparatus for reducing power supply noise in an integrated circuit under test resulting from state transitions of the logic it implements.

Description of Related Art

[0003] An integrated circuit (IC) tester can concurrently test a set of ICs in the form of die on a silicon wafer. FIG. 1 is a block diagram illustrating a typical IC tester 10 connected through a probe card 12 to a set of similar IC devices under test (DUTs) 14. Tester 10 uses pogo pins 15 or other means to connect various input and output terminals to a set of contacts 16 on probe card 12. Probe card 12 includes a set of probes 18 for contacting input/output (I/O) pads 19 on the surface of each DUT 14 and provides conductive paths 20 linking contacts 16 to probes 18. The paths through probe card 12 allow tester 10 to transmit test signals to DUT 14 and to monitor output signals produced by the DUT. Digital integrated circuits often include synchronous logic gates clocked in response to pulses of a periodic master clock signal (CLOCK). Therefore probe card 12 also provides a path 22 through which tester 10 may supply a CLOCK signal to each DUT 14. The test system also includes a power supply 24 for supplying power to DUTs 14 as they are being tested. Probe card 12 connects power supply 24 to a power input pad 26 of each DUT 14 through probes 18.

[0004] Each switching transistor within a DUT 14 has an inherent input capacitance, and in order to turn on or off the transistor, the transistor's driver must either charge or discharge the transistor's input capacitance. When a driver charges a transistor's input capacitance it draws charging current from power supply 24. Once the transistor's input capacitance is fully charged, its driver need only supply a relatively small amount of leakage current needed to keep the transistor's input capacitance charged so that the transistor remains turned on or off. In DUTs implementing synchronous logic, most transistor switching occurs immediately after an edge of each CLOCK signal pulse. Thus immediately after each pulse of the CLOCK signal, there is a temporary increase in the power supply current I_1 input to each DUT 14 to provide the charging current necessary to change the switching states of various transistors within the DUT. Later in the CLOCK signal cycle, after those transistors have changed state, the demand for power supply current I_1 falls to a "quiescent" steady state level and remains there until the beginning of the next CLOCK signal cycle.

[0005] The signal paths 28 through which probe card 12 connects power supply 24 to each DUT 14 have an inherent impedance represented in FIG. 1 by a resistance R_1 . Since there is a voltage drop between the output of power supply 24 and the power input 26 of DUT 14, the supply voltage input V_B to DUT 14 is somewhat less than the output voltage V_A of power supply 24, and although V_A may be well-regulated, V_B varies with the magnitude of current I_1 . After the start of each CLOCK signal cycle, the temporary increase in I_1 needed to charge switching transistor input capacitance increases the voltage drop across R_1 , thereby temporarily reducing V_B . Since the dip in supply voltage V_B occurring after each CLOCK signal pulse edge is a form of noise that can adversely affect the performance of DUTs 14, it is desirable to limit its magnitude and duration. We can limit that noise by reducing the reactance of the paths 28 between power supply 24 and DUTs 14, for example by increasing conductor size or by minimizing the length of path 28. However there are practical limits to the amount by which we can reduce that reactance.

[0006] We can also reduce power supply noise by placing a capacitor C_1 on probe card 12 near the power supply input 26 of each DUT 14. FIG. 2 illustrates the behavior of supply voltage V_B and current I_1 at the power input 26 of IC 14 in response to a pulse of the CLOCK signal input to IC 14 when capacitor C_1 is

insufficiently large. Note that the temporary rise in I1 above its quiescent level IQ following an edge of the CLOCK signal at time T1 produces a temporary increase in voltage drop across R1 that in turn produces a temporary dip in supply voltage VC below its quiescent level VQ.

[0007] FIG. 3 illustrates the behavior of VB and I1 when capacitor C1 is sufficiently large. Between CLOCK signal pulses, when DUT 14 is quiescent, capacitor C1 charges to the quiescent level VQ of VB. Following a rising (or falling) edge of the CLOCK signal at time T1, when a DUT 14 temporarily demands more current, capacitor C1 supplies some its stored charge to DUT 14 thereby reducing the amount of additional current power supply 24 must provide to meet the increased demand. As may be seen in FIG. 3, the presence of C1 reduces the magnitude of the temporary voltage drop across R1 and therefore reduces the magnitude of the dip in the supply voltage VB input to the DUT 14.

[0008] For capacitor C1 to adequately limit variation in VB, the capacitor must be large enough to supply the needed charge to DUT 14 and must be positioned close to DUT 14 so that the path impedance between C1 and DUT 14 is very low. Unfortunately it is not always convenient or possible to mount a large capacitor on a probe card 12 near the power supply input terminal 26 of each DUT 14. FIG. 4 is a simplified plan view of a typical probe card 12. IC tester 10 resides above the probe card and the wafer containing DUTs 14 is held below the probe card. Since the I/O terminals of IC tester 10 of FIG. 1 are distributed over a relatively large area compared to the surface area of the wafer being tested, probe card 12 provides a relatively large upper surface 25 for holding the contacts 16 the tester accesses. On the other hand, the probes 18 (not shown) on the underside of probe card 12 that contact DUTs 14 on the wafer are concentrated under a relatively small central area 27 of probe card 12.

[0009] The path impedance between contacts 16 on the upper surface 25 of card 12 and the probes 18 under area 27 is a function of the distance between each contact 16 and its corresponding probe. To minimize the distance between capacitors C1 and the DUTs, the capacitors should be mounted on probe card 12 near (or above) the small central area 27. However when a wafer includes a large number of ICs to be tested or an IC having a large number of densely packed

terminals, there is not enough space to mount the required number of capacitors C1 of sufficient size sufficiently close to central area 27.

Summary of the Invention

[0010] During a test of an integrated circuit device under test (DUT) employing synchronous logic, the DUT experiences a temporarily increase in its demand for power supply current after each pulse of a clock signal input to the DUT because each clock signal pulse initiates state transitions of clocked logic devices within the DUT. The DUT needs the extra current to charge input capacitance of transistors forming those logic devices. It is an object of the invention to provide a means for limiting variation in power supply voltage at the power input terminal of a DUT arising from the transient increase in power supply current following each clock signal pulse, thus reducing the power supply noise at the DUT.

[0011] In accordance with one aspect of the invention, a charging current is supplied to the DUT's power input terminal from an auxiliary power supply source after each clock signal pulse to supplement a current continuously supplied by a main power supply during the test. The additional charging current reduces the need for the main power supply to increase its output current to meet the DUT's increased demand. With the output current of the main power supply being held substantially constant despite the DUT's increased demand for current, any voltage drop across path impedance between the main power supply and the DUT remains substantially constant. Thus the supply voltage at the DUT's power input terminal remains substantially constant.

[0012] The amount of additional charging current a DUT requires after each clock signal pulse varies depending on the state transition its internal logic devices undergoes in response to the clock signal pulse. In accordance with another aspect of the invention the additional charging current supplied is adjusted to match a predicted value of transient charging current required by the DUT following each clock signal pulse.

[0013] In accordance with a further aspect of the invention, in a preferred embodiment thereof, the auxiliary power source includes a capacitor, a transistor switch and a voltage source. The voltage source charges the capacitor before each clock signal pulse and the switch temporarily connects the capacitor to the

DUT's power input terminal at the start of each clock cycle so that the capacitor can deliver its charge to the DUT to provide the DUT's required transient charging current. The voltage to which the capacitor is charged is adjusted prior to the start of each clock signal cycle so that the capacitor delivers the amount of charge the DUT is predicted to require during the next state change. The system can regulate the DUT's supply voltage even when there is significant path impedance between the capacitor and the DUT. Thus the capacitor may be mounted on a probe card relatively distant from DUT.

[0014] In accordance with a further aspect of the invention, in an alternative embodiment thereof, a DUT and a reference IC similar to the DUT are tested at the same time. However the reference IC is tested slightly in advance of the DUT so that variations in the input power supply voltage of the reference IC due to changes in its current demand predict subsequent similar variations in the input current demand of the DUT. An amplifier amplifies variations in the voltage at the power input terminal of the reference IC to produce the time-varying charging current needed by the DUT. The lag between the tests performed on the reference DUT and the second DUT is adjusted to match a signal path delay through the amplifier and interconnect path.

[0015] In accordance with yet a further aspect of the invention, a supplemental current is supplied to the power input terminal. The amount of the supplemental current is related to an amount of additional current temporarily drawn by the power input terminal.

[0016] The concluding portion of this specification particularly points out and distinctly claims the subject matter of the present invention. However those skilled in the art will best understand both the organization and method of operation of the invention, together with further advantages and objects thereof, by reading the remaining portions of the specification in view of the accompanying drawing(s) wherein like reference characters refer to like elements.

Brief Description of the Drawing(s)

[0017] FIG. 1 is a block diagram illustrating a typical prior art test system including an integrated circuit tester connected through a probe card to a set of integrated circuit devices under test (DUTs),

[0018] FIGS. 2 and 3 are timing diagrams illustrating behavior of signals within the prior art test system of FIG. 1,

[0019] FIG. 4 is a simplified plan view of the prior art probe card of FIG. 1,

[0020] FIG. 5 is a block diagram illustrating a test system implementing a system for reducing noise in the power supply inputs of a set of DUTs in accordance with a first embodiment of the present invention;

[0021] FIG. 6 is a timing diagram illustrating behavior of signals within the test system of FIG. 5,

[0022] FIG. 7 is a block diagram illustrating operation of the test system of FIG. 5 during a calibration procedure;

[0023] FIG. 8 is a simplified plan view of the probe card of FIG. 6;

[0024] FIGS. 9 and 10 are block diagrams illustrating test systems implementing second and third embodiments of the present invention;

[0025] FIG. 11 is a timing diagram illustrating behavior of signals within the test system of FIG. 10;

[0026] FIGS. 12 is a block diagram illustrating a test system implementing a fourth embodiment of the present invention;

[0027] FIG. 13 is a timing diagram illustrating behavior of signals within the test system of FIG. 12;

[0028] FIG. 14 is a block diagram illustrating a fifth embodiment of the present invention;

[0029] FIG. 15 is a block diagram illustrating a sixth embodiment of the present invention;

[0030] FIG. 16 is a block diagram illustrating a seventh embodiment of the present invention; and

[0031] FIG. 17 is a timing diagram illustrating behavior of signals within the circuit of FIG. 16.

[0032] FIG. 18 is a block diagram illustrating an eighth embodiment of the invention.

[0033] FIG. 19 is a block diagram illustrating a ninth embodiment of the invention.

[0034] FIG. 20A illustrates an exemplary probe card.

[0035] FIG. 20B illustrates another exemplary probe card.

Description of the Preferred Embodiment(s)

System Architecture

[0036] FIG. 5 illustrates in block diagram form an integrated circuit (IC) tester 30 linked through a probe card 32 to a set of similar IC devices under test (DUTs) 34 in the form of die on a semiconductor wafer. Probe card 32 includes a set of probes 37 for accessing input/output terminal pads 39 on the surfaces of DUTs 34 and also includes signal paths 46 linking tester 30 to probes 37 to allow IC tester 30 to send a clock signal (CLOCK) and other test signals to DUTs 34 and to convey DUT output signals back to tester 30 so that the tester can monitor the behavior of the DUTs.

[0037] Probe card 32 also links a main power supply to a power input terminal 41 of each DUT 34 via probes 37. Power supply 36 produces a well-regulated output voltage V_A and continuously supplies a current I_2 to DUT 34. For illustrative purposes, FIG. 5 represents the inherent impedances of the paths 43 through probe card 32 between main power supply 36 and each DUT 34 as resistors R_1 . Due to a voltage drop across resistor R_1 , the input supply voltage V_B to each DUT 34 is always somewhat less than V_A .

[0038] In accordance with the invention, a first transistor switch SW_1 mounted on probe card 32 links an auxiliary power supply 38 to a set of capacitors C_2 mounted in probe card 32. A set of second transistor switches SW_2 also mounted on probe card 32 link each capacitor C_2 to the power input terminal of a corresponding DUT 34. A resistor R_2 shown in FIG. 5 represents the inherent signal path impedance within probe card 32 between each capacitor C_1 and the power input terminal 41 of a DUT 34 when switch SW_2 is closed. IC tester 30 provides an output control signal CNT_1 for SW_1 , a control signal CNT_2 for controlling switches SW_2 and control data CNT_3 for controlling the magnitude of the output voltage V_C of auxiliary power supply 38. As discussed in detail below, auxiliary power supply 38, switches SW_1 and SW_2 and capacitors C_2 act as an

auxiliary current source to inject current I3 into the power input terminal 41 of each DUT under control of IC tester 30.

Power Supply Noise

[0039] DUTs 34 implement synchronous logic in which switching transistors forming logic gates turn on and off in response to pulses of the periodic master CLOCK signal provided by tester 30. Each switching transistor has an inherent input capacitance, and in order to turn on or off the transistor, its driver must either charge or discharge the transistor's input capacitance. When drivers within DUTs 34 charge a transistor's input capacitance they increase the amount of current I1 that must be supplied to each DUT's power input terminal 41. Once the transistor's input capacitance is fully charged, its driver need only supply the relatively small amount of leakage current needed to keep the transistor's input capacitance charged so that the transistor remains turned on or off. Thus immediately after each pulse of the CLOCK signal, there is a temporary increase in the power supply current I1 input to each DUT 34 to provide the charging current necessary to change the switching states of various transistors. Later in a CLOCK signal cycle, after those transistors have changed state, the demand for power supply current falls to a "quiescent" steady state level and remains there until the beginning of the next CLOCK signal cycle. The amount of additional current I1 a DUT 34 needs at the start of each CLOCK signal cycle depends on the number and nature of transistors that turn on or off during that particular CLOCK signal cycle.

[0040] If tester 30 always kept switches SW1 and SW2 open, main power supply 36 would always provide all of the current input I1 to each DUT 34. In such case the temporary increase in supply current I1 due to the increased switching activity within each DUT 34 after each CLOCK signal pulse would cause a temporary increase in the voltage drop across the inherent impedance R1 of the signal path 43 between main power supply 36 and DUT 34. This in turn would cause a temporary decline in the voltage VB at the DUT's power input terminal 41. FIG. 2 represents the behavior of VB and I1 when SW2 is always open. Since the dip in supply voltage VB occurring after each CLOCK signal pulse edge is a form of noise that can adversely affect the performance of DUTs 34, it is desirable to limit the magnitude of that voltage dip.

Predictive Charge Compensation

[0041] In accordance with the invention, IC tester 30 controls auxiliary power supply 38 and the states of switches SW1 and SW2 so that capacitor C2 supplies additional charging current I3 to DUT 34 at the start of each test cycle. The charging current I3, which only flows during an initial portion of each CLOCK signal cycle, combines with the current I2 output of the main power supply to provide the current input I1 to DUT 34. When charging current I3 provides approximately the same amount of charge the capacitance of switching transistors within DUT 34 acquire following a CLOCK signal pulse, there is relatively little change in the current I2 produced by main power supply 36 following the CLOCK signal pulse and therefore very little variation in supply voltage VB.

[0042] Thus prior to each CLOCK signal pulse, tester 30 supplies data CNT3 to auxiliary power supply 38 indicating a desired magnitude of VC and then closes switch SW1. Power supply 38 then charges all capacitors C2. The amount of charge capacitors C2 store is proportional to the magnitude of VC. When capacitors C2 have had time to fully charge, tester 30 opens switch SW1. Thereafter, at the start of the next CLOCK signal cycle, tester 30 closes all switches SW2 so that charge stored in capacitors C2 can flow as currents I3 into DUTs 34. Thereafter, when the need for transient charging current has passed, tester 30 opens switches SW2 so that only main power supply 36 supplies current to DUTs 34 during the remaining portion of the CLOCK signal cycle. This process repeats during every cycle of the CLOCK signal.

[0043] FIG. 6 illustrates the behavior of supply voltage VB, and currents I1, I2 and I3 during an initial portion of a CLOCK signal cycle. Current I1 exhibits a large temporarily increase above its quiescent level IQ1 after an edge of the CLOCK pulse at time T1 to charge capacitance within the DUT 34. Current I3 rises quickly to provide substantially all the additional charging current. The output current I2 of main power supply 38 exhibits only a relatively small perturbation from its quiescent value IQ2 resulting from small mismatches between I3 and the transient component of I2. Since the variation in I2 is small, the variation in VB is small. Thus the present invention substantially limits the power supply noise due to switching transients in DUTs 34.

Tester Programming

[0044] As mentioned above, the amount of additional charging current each DUT 34 draws at the start of a CLOCK signal cycle depends on the number of transistors that turn on or off during the CLOCK signal cycle and charging current varies from cycle-to-cycle. In order to provide proper voltage regulation at DUT terminal 41, tester 30 has to predict how much charge DUT 34 is going to store following the each CLOCK signal pulse because it has to adjust the magnitude of auxiliary power supply output VC so that capacitors C2 store the proper amount of charge prior to each CLOCK signal cycle.

[0045] FIG. 7 depicts a test system set up that allows tester 30 to experimentally determine the level to which it should set VC for each test cycle. A reference DUT 40 that is known to operate properly and which is similar to the ICs to be tested, is connected to tester 30 via probe 32 in generally the same way DUTs 34 are to be connected so that tester 30 can perform the same test on reference IC 40. However probe card 32 also links the power supply terminal of reference IC 40 to an input terminal of tester 30 so that tester 30 can monitor the power supply voltage VB. Tester 30 then executes only the first CLOCK cycle of the test while observing VB using the minimum value for VC. If VB falls below a desired lower limit during the CLOCK signal cycle, tester 38 repeats the first CLOCK signal cycle of the test using a higher value of VC. This process is repeated iteratively until an appropriate value of VC for the first CLOCK signal cycle is established. The tester then iteratively executes the first two CLOCK signal cycles of the test while monitoring VB during the second CLOCK signal cycle and adjusting VC accordingly. The same procedure is used to establish an appropriate value of VC for each successive CLOCK signal cycle of the test. Those values for VC may then be used when testing DUTs 34.

[0046] Designers typically use circuit simulators to simulate ICs before they are fabricated. When a circuit simulator performs the same test on simulated ICs that an IC tester would perform on its real counterpart, the circuit simulator can be employed in an analogous manner to determine the sequence of VC values to be used during a test of the real IC.

Probe Card

[0047] FIG. 4 illustrates a typical prior art probe card 12 that connects voltage regulating capacitors C1 to the power input terminals of DUTs to limit power supply noise. Such probe cards must minimize the distance between voltage regulating capacitors and the DUTs so as to minimize the impedance between the capacitors and the DUTs. Thus the capacitors preferably are mounted on the probe card in or near a small area 27 above the probes that access the DUTs. Since there is little space on the probe card near the probes, the size and number of regulating capacitors C1 that can be deployed on probe card 12 is limited. This limitation on capacitor mounting space can limit the number of DUTs that can be concurrently tested.

[0048] FIG. 8 is a simplified plan view of the probe card 32 of FIG. 5 in accordance with the invention. Contact points 45 accessed by IC tester 30 of FIG. 7 are distributed over a relatively large area of the upper surface 43 of probe card 32 while the probes 37 (not shown) that contact DUTs 34 are concentrated under a relatively small central area 47 of the probe card. Since the voltage VC to which capacitors C2 are charged can be adjusted to accommodate significant path impedance R2 (FIG. 5) between any switch SW2 and terminal 41 of DUT 34, capacitors C2 can be mounted on probe card 32 at a significantly greater distance from central area 47 above the DUT probes than capacitors C1 of FIG. 4. Also since capacitors C2 are charged to a higher voltage than capacitors C1, they can be smaller than capacitors C1. Since capacitors C2 of probe card 32 of FIG. 8 can be smaller and further from the center of the probe card than capacitors C1 of the prior art probe card 12 of FIG. 4, a larger number of capacitors C2 can be mounted on probe card 32. Thus a test system employing probe card 32 in accordance with the invention can concurrently test more DUTs than a test system employing a prior art probe card 12 of FIG. 4.

Probe Card With On-Board Pattern Generator

[0049] FIG. 9 illustrates an alternative embodiment of the invention including a probe card 50 generally similar to probe card 32 of FIG. 7 except that it has mounted thereon a "power control IC" 52. Power control IC 52 includes a pattern generator 54 that carries out the pattern generation function of IC tester 30 of FIG. 7 with respect to producing the control signals and data CNT1, CNT2 and CNT3 for controlling switches SW1 and SW2 and auxiliary power supply 38. Power control

IC 52 includes a conventional pattern generator 54 programmed before the start of a test by externally generated programming data provided via a conventional computer bus 56. Pattern generator 54 begins generating its output data pattern in response to a START signal from an IC tester 58 marking the start of a test and produces its output CNT1, CNT2, CNT3 data pattern in response to the same system clock (SYSCLK) that clocks operations of tester 58.

[0050] When the required capacitance C2 is sufficiently small, switches SW1 and SW2 and capacitors C2 may be implemented within power control IC 52 as shown in FIG. 9. IC 52 should be mounted on the probe card as near as possible to the DUT probes. Merging switches SW1 and SW2 and capacitors C2 and the pattern generation function of tester 30 into a single IC 52 reduces the cost and complexity of probe card 32 and reduces the required number of tester 30 output channels. However when necessary capacitors C2 can be implemented by discrete components external to power control IC 52.

Pulse Width Modulated Charge Flow

[0051] FIG. 10 illustrates an embodiment of the invention that is generally similar to the embodiment of FIG. 5. However in FIG. 10 switch SW1 is omitted from probe card 60 so that the VC output of auxiliary power supply 38 is directly connected to capacitors C2. Also the output voltage VC is fixed and not adjusted by IC tester 30 so that C2 charges to the same value prior to each CLOCK signal pulse. In this configuration IC tester 30 controls the amount of charge capacitors C2 deliver to DUTs 34 at the start of each CLOCK pulse by pulse width modulating switches SW2 via control signal CNT2. The amount of time tester 30 closes switches SW2 following the leading edge of a CLOCK signal pulse determines the amount of charge capacitors C2 deliver to DUTs 34. Alternatively, the shape of the I3 current flow illustrated in FIG. 6 can be more closely approximated when tester 30 rapidly increases and then decreases the duty cycle of the CNT2 signal as illustrated in FIG. 11.

Analog Modulated Charge Flow

[0052] FIG. 12 illustrates an embodiment of the invention that is generally similar to the embodiment of FIG. 10. However in FIG. 12 the transistor switches SW2 are replaced with transistors Q2 operated in their active regions when DUTs 34 are undergoing state changes and require additional current I3. In this

configuration, the CNT2 output of IC tester 30 is a data sequence applied as input to an analog-to-digital (A/D) converter 63 mounted on probe card 61. The data sequence CNT2 represents a predicted demand for charging current I3 during each CLOCK signal cycle. A/D converter 63 responds to the CNT2 data sequence by producing an analog signal CNT4 input to the bases of transistors Q2 that varies during each CLOCK signal cycle as illustrated in FIG. 13. Analog signal CNT4 controls the amount of current I3 each transistor Q2 allows to flow out of a capacitor C2 so that it substantially matches the predicted transient component of the current I1 demanded by DUT 34. A/D converter 63 may be implemented within IC tester 30 instead of being mounted on probe card 61.

Charge Prediction Using Reference DUT

[0053] FIG. 14 illustrate an embodiment of the invention wherein a reference DUT 60 similar to DUTs 34 is tested in a similar way except that tester 30 tests the reference DUT 60 slightly in advance of the other DUTs by advancing the CLOCK and other input signals it supplies to reference DUT 60. A main power supply 62 powers all DUTs 34 while an auxiliary power supply 64 powers reference DUT 60. A capacitor C4 mounted on probe card 66 near reference DUT 60 regulates the voltage VREF at its power input terminal 68 in a conventional manner so that it stays within its allowed operating range. A capacitor C5 links VREF to a set of amplifier's A1, and a capacitor C6 links the output of each amplifier A1 to the power input terminal 70 of each DUT 34.

[0054] Though well-regulated, the supply voltage VREF at the input terminal 68 of reference DUT 60 falls below its quiescent level by a small amount following the start of each CLOCK signal cycle due to the reference DUT's transient charging current demand. The amount of voltage decline in VREF is proportional to the amount of transient charging current drawn by reference DUT 60. Since reference DUT 60 is similar to DUTs 34 and is tested slightly in advance of DUTs 34, a decline in VREF predicts the amount of transient charging current each DUT 34 a short time later.

[0055] Amplifiers A1, acting through capacitors C5 and C6, amplify the AC component of VREF to produce output currents I3 that augment the current outputs I2 of main power supply 62 to provide the current input I1 to each DUT 34. The amount of time by which tester 30 advances the test of reference DUT 60 is set to

equal the delay between variations in reference voltage VREF and corresponding variations in currents I3. With the (negative) gain of each amplifier A1 appropriately adjusted by an externally generated signal (GAIN), currents I3 will substantially match the transient charging currents required by DUTs 34.

Charge Prediction In Non-Testing Environments

[0056] In addition to being useful for reducing power supply noise when testing integrated circuits, embodiments of the present invention can also be employed to reduce power supply noise in application in which an integrated circuit passes through a succession of states that can be predicted.

[0057] FIG. 15 illustrates an example embodiment of the invention in which an integrated circuit 80 passes through a predictable succession of states in response to edges of an externally generated CLOCK signal supplied as input thereto. IC 80 receives power from a main power supply 82. An auxiliary power supply 84 charges a capacitor C2 via a switch SW1 when switch SW1 is closed. Capacitor C2 supplies its charge as additional current input to IC 80 when a switch SW2 is closed. A "charge predictor" circuit 86 responds to the CLOCK signal by asserting a signal CNT1 to close switch SW1 and deasserting a control signal CNT2 to open switch SW2 during a portion of each CLOCK signal cycle in which IC 80 is not changing state. This allows auxiliary power supply 84 to charge capacitor C2 between state changes. Charge predictor circuit 86 asserts control signal CNT2 to close switch SW2 and deasserts control signal CNT1 to open switch SW1 during a portion of each CLOCK signal cycle in which IC 80 is changing state, thereby allowing capacitor C2 to deliver current to the power input of IC 80 to provide its transient current needs. Charge predictor 86 also provides control data CNT2 to auxiliary power supply 84 to adjust its output voltage VC so that it charges capacitor C2 to a level determined in accordance with an amount of current IC 80 is expected to draw during a next state change. Charge predictor 86 is suitably implemented by a conventional pattern generator or any other device capable of producing output data sequences CNT1, CNT2 and CNT3 that are appropriate for transient current requirements of IC 80 for its expected sequence of states. Switches SW1 and SW2 and/or capacitor C2 may be implemented either external to IC 80 as illustrated in FIG. 15 or may be implemented internal to IC 80.

Charge Averaging

[0058] FIG. 16 illustrates a simple version of the invention suitable for use in applications wherein the amount of charging current an IC 80 is expected to draw at the start of each CLOCK signal cycle lies within a relatively limited, predictable range. As shown in FIG. 16, an inverter 90 inverts the CLOCK signal to provide the CNT1 control signal input to a switch SW1 coupling a main power supply to a capacitor C2. The CLOCK signal directly provides a CNT2 control signal input to a switch SW2 connecting capacitor C2 to a power input of IC 80 normally driven by a main power supply 82. As illustrated in FIG. 17, the CLOCK signal drives the CNT2 signal high to close switch SW2 during a first half of each CLOCK signal cycle and drives CNT1 high to close switch SW1 during a second half of each CLOCK signal cycle.

[0059] The output voltage VC of auxiliary power supply 84 is set to a constant value so that it charges capacitor C2 to the same level prior to the start of each CLOCK signal cycle. The level of VC is set to appropriately position the range over which power supply input voltage VB swings when IC 80 is drawing additional charging current at the start of each CLOCK signal cycle. For example when we want the quiescent value of VB to lie at the middle of its range, we can adjust VC so that capacitor C2 supplies an amount of charging current that is in the middle of the range of charging currents IC 80 is expected to draw. On the other hand, if we want to prevent VB from falling much below its quiescent value but are willing to allow VB to rise above its quiescent value, we can adjust VC so that capacitor C2 supplies the maximum amount of charging current IC 80 is expected to draw. While capacitor C2 may supply too little charging current during some CLOCK signal cycles and too much charging current during other CLOCK signal cycles, in many applications the system illustrated in FIG. 16 nonetheless can keep the swings in VB within acceptable limits when VC is suitably adjusted. Note that the systems of FIGS. 5, 9, 14 and 15 can be programmed to operate in a similar manner by setting control data CNT3 to the same value for every CLOCK signal cycle.

[0060] FIG. 18 illustrates another exemplary embodiment. As shown in FIG. 18, a power supply 36 provides power through a probe card 50 to a power input terminal 1806 on a semiconductor device under test (DUT) 34. A representation of

the inherent impedance through power line 1812 on the probe card 50 is illustrated in FIG. 18 as R1. As also shown in FIG. 18, an IC tester 58 provides clock and other signals through the probe card 50 to the DUT 34. A clock input terminal on exemplary DUT 34 is illustrated as terminal 1808. The IC tester 58 also receives signals through the probe card 50 from the DUT 34. One input/output (I/O) terminal 1810 is shown on DUT 34 in FIG. 18. However, DUT 34 may have additional I/O terminals 1810 or may have terminals dedicated solely to inputs and other solely to outputs or a combination of terminals dedicated to solely inputs or outputs and other terminals that function as both input and output terminals. It should be apparent that probe card 50 may make connections with one DUT as shown in FIG. 18 or a plurality of DUTs, for example, as shown in FIG. 14.

[0061] As shown in FIG. 18, a current sensing device 1804 (e.g., a current sense coupler or a current transformer) senses current through bypass capacitor C1. Amplifier 1802, which is preferably an inverting amplifier (e.g., the amplifier has a gain of minus one) provides current through capacitor C7 into transmission line 1812. An auxiliary power supply 38 provides power to amplifier 1802. Of course, power may be supplied to amplifier 1802 by other means, including from power supply 36, IC tester 58, a power supply located on the probe card 50, or a power supply located other than with the power supply 36, IC tester 58, or probe card 50.

[0062] In operation, power terminal 1806 typically draws little current, as described above (assuming DUT 34 includes primarily field effect transistors). Only under certain circumstances does power terminal 1806 draw a significant amount of current. As discussed above, the most common of these circumstances arises when at least one transistor in DUT 34 changes state, which typically occurs in correspondence with a rising or falling edge of the clock at clock terminal 1808.

[0063] While DUT 34 is not changing states, the small amount of current drawn at power terminal 1806 typically results in only a small and predominantly static direct current (DC) flow or no current flow through bypass capacitor C1. This results in little to no current sensed by current sensing device 1804, and consequently little to no current from inverting amplifier 1802.

[0064] While DUT 34 is changing states, however, power terminal 1806 temporarily draws a significant amount of current, as described above. This results in a temporary significant and changing flow of current through bypass capacitor

C1, as described above. That current is sensed by current sensing device 1804 and inverted and amplified by inverting amplifier 1802 and ultimately provided through isolation capacitor C7 into power line 1812. As described above, this extra current provided on power line 1812 by amplifier 1802 reduces variations in the voltage at power terminal 1806.

[0065] FIG. 19 illustrates a variation of the exemplary embodiment shown in FIG. 18. As shown, FIG. 19 is generally similar to FIG. 18 and also includes a current sensing element 1804 and an inverting amplifier 1802 configured to provide current to power line 1812 on probe card 50. However, in FIG. 19, the current sensing element 1804 senses current flow through the power line 1812 rather than through bypass capacitor C1.

[0066] FIG. 19 operates similarly to FIG. 18. That is, while DUT 34 is not changing states, the typically small, predominately static direct current (DC) drawn at power terminal 1806 and thus through power line 1804 results in little to no current sensed by current sensing device 1804 and, consequently, little to no current from inverting amplifier 1802.

[0067] While DUT 34 is changing states, however, the significant and changing amount of current drawn at power terminal 1806 and thus through power line 1804 is sensed by current sensing device 1804 and inverted and amplified by inverting amplifier 1802 and ultimately provided through isolation capacitor C7 into power line 1812. As described above, this extra current provided on power line 1812 by amplifier 1802 reduces variations in the voltage at power terminal 1806.

[0068] It should be apparent that the probe card illustrated in any of the above-described embodiments may be of just about any construction or design. For example, FIG. 20A illustrates a relatively simple probe card comprising a substrate 2002 with terminals 2004 for connecting to an IC tester (not shown in FIG. 20A) and probe elements 2008 for making electrical connections with a DUT (not shown in FIG. 20A). As shown, terminals 2004 are electrically connected to probe elements 2008 by interconnect elements 2006.

[0069] Substrate 2002 may be, for example, a single or multilayered printed circuit board or ceramic or other material. It should be apparent that the material composition of the substrate is not critical to the invention. Probes elements 2008 may be any type of probe capable of making electrical connections with a DUT including without limitation needle probes, COBRA style probes, bumps, studs,

posts, spring contacts, etc. Nonlimiting examples of suitable spring contacts are disclosed in U.S. Patent No. 5,476,211, U.S. Patent Application Serial No. 08/802,054, filed February 18, 1997, which corresponds to PCT publication WO 97/44676, U.S. Patent No. 6,268,015 B1, and U.S. Patent Application Serial No. 09/364,855, filed July 30, 1999, which corresponds to PCT publication WO 01/09952, which are incorporated by reference herein. Such spring contacts may be treated as described in U.S. Patent No. 6,150,186 or U.S. Patent Application Serial No. 10/027,476, filed December 21, 2001, which are also incorporated by reference herein. Alternatively, the "probes" may be pads or terminals for making contact with raised elements on the DUT, such as spring contacts formed on the DUT. Nonlimiting examples of interconnection paths 2006 include vias and/or a combination of vias and conductive traces located on a surface of substrate 2002 or within substrate 2002.

[0070] FIG. 20B illustrates another nonlimiting example of a probe card that may be used with the present invention. As shown, the exemplary probe card shown in FIG. 20B includes a substrate 2018, an interposer 2012, and a probe head 2032. Terminals 2022 make contact with an IC tester (not shown in FIG. 20B) and probe elements 2034, which may be similar to probe elements 2008 discussed above, make contact with a DUT (not shown in FIG. 20B). Interconnection paths 2020, resilient connection elements 2016, interconnection paths 2014, resilient connection elements 2010, and interconnection paths 2036 provide electrically conductive paths from terminals 2022 to probe elements 2034.

[0071] Substrate 2018, interposer 2012, and probe head 2032 may be made of materials similar to those described above with regard to 2002. Indeed, the material composition of the substrate 2018, the interposer 2012, and the probe head 2032 are not critical to the invention, and any composition may be used. Interconnection paths 2020, 2014, 2036 may be similar to interconnection paths 2006 as described above. Resilient connection elements 2016 and 2010 are preferably elongate, resilient elements. Nonlimiting examples of such elements are illustrated in U.S. Patent No. 5,476,211; U.S. Patent Application Serial No. 08/802,054, filed February 18, 1997, which corresponds to PCT publication WO 97/44676; U.S. Patent No. 6,268,015 B1; and U.S. Patent Application Serial No. 09/364,855, filed July 30, 1999, which corresponds to PCT publication WO 01/09952, all of which have been incorporated by reference herein. A more

detailed discussion of an exemplary probe card comprising a plurality of substrates, such as those shown in FIG. 20B, is found in U.S. Patent No. 5, 974,662, which is incorporated by reference herein. Many variations of the exemplary design shown in FIG. 20B are possible. As just one example, interconnection path 2014 may be replaced with a hole and one or more resilient elements 2016 and/or 2010 fixed within the hole and extending out of the hole to make contact with substrate 2018 and probe head 2032.

[0072] It should be apparent, however, that the construction or design of the probe card is not critical to the invention and any construction or design may be used. As shown in the embodiments described herein, circuitry for reducing variations in the voltage at a power terminal on a DUT is preferably disposed on the probe card. If a multisubstrate probe card is used, such as the exemplary probe shown in FIG. 20B, the circuitry may be located on any one of the substrates or may be distributed among two or more of the substrates. Thus, for example, the circuitry may be located on one of the probe head 2032, interposer 2012, or substrate 2018 illustrated in FIG. 20B, or the circuitry may be located on a combination of two or more of the probe head, the interposer, and/or the substrate. It should be apparent that the circuitry may be formed entirely of interconnected discrete circuit elements, may be formed entirely on an integrated circuit, or may consist in part of discrete circuit elements and in part of elements formed on an integrated circuit.

[0073] Thus has been shown and described a system for limiting power supply noise of an integrated circuit device when it is being tested. While the forgoing specification has described preferred embodiment(s) of the present invention, one skilled in the art may make many modifications to the preferred embodiment without departing from the invention in its broader aspects. While the invention is illustrated herein as reducing noise in a system employing only a single main power supply, it will be appreciated that the invention can be employed in environments in which more than one main power supply provide power to DUTs. Also while the apparatus is illustrated as operating in connection with DUTs having a single power input, it will be appreciated that the apparatus can be adapted to operate in connection with DUTs having multiple power inputs. For example referring to FIG. 7, if each DUT 34 had more than one power supply input terminal 41, an additional auxiliary power supply 38, an additional capacitor C2 and

additional switches SW1 and SW2 would be provided for each additional DUT power input terminal. Also, it should be noted that while the apparatus is described as providing additional charging current following a leading edge of a CLOCK signal pulse, it may be easily adapted to provide additional charging current following a trailing edge of the CLOCK signal pulse for use with DUTs that switch on trailing CLOCK signal edges. The appended claims therefore are intended to cover all such modifications as fall within the true scope and spirit of the invention.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227